

# ***USB KVM Switch***

*User's Manual*

## *I. Introduction:*

This USB KVM Switch allow you to control up to two or four computers from one USB Keyboard, USB Mouse, Video Monitor.


## *II. Features:*

- ★ USB bus powered
- ★ Fully compliant with USB 1.1 specifications and delivers a 12Mbps data transmission rate
- ★ USB hot keys and direct-access port selectors for easy manual switching
- ★ LED display for easy status monitoring
- ★ No drivers or firmware required for Windows and Mac OS

### *III. Specifications:*


Function	Specification	
Description	2PC TO 1 USER	4PC TO 1 USER
PC side Connector	HD-15M x2 , USB B type x 2	HD-15M x4 , USB B type x 4
Console side Connector	HD-15F x 1,USB A type x 2	
Max. Resolution	1920 x 1200	
Bandwidth	250GHz	
Signal Type	USB 1.1	
Operating Temperature	0-40 degrees(Celsius)	
Storage Temperature	-5-70 degrees(Celsius)	
Humidity	0-80%RH, Non-condensing	
Housing	Metal	

## *IV. Introduction:*



Number	Feature	Function
1	USB A Type x 1	Connector USB Mouse
2	HD-15F	Connector Monitor
3	USB A Type x 1	Connector USB Keyboard
4	Manual LED	Active
5	Switch button	Select PC
6	PC1 Cable	Connector PC1
7	PC2 Cable	Connector PC2

## V. Installation:



## VI. Keyboard hot key:

Hot Key Definition	
Scroll + Scroll + 1	Switch to PC1
Scroll + Scroll + 2	Switch to PC2
Scroll + Scroll + or → ↓	Switch to Next PC
Scroll + Scroll + or ← ↑	Switch to Previous PC
Scroll + Scroll + B	Beeper on/off
Scroll + Scroll + S	Auto-scan mode every 10 second

After shot down each PC, please switch to ther other one before the power shot down

## *VII. Limited Warranty:*

IN NO EVENT THE DIRECT VENDOR'S LIABILITY EXCEED THE PRICE PAID THE PRODUCT FROM DIRECT, INDIRECT, SPECIAL, INCIDENTAL, OR CONSEQUENTIAL DAMAGES RESULTING FROM THE USE OF THE PRODUCT, DIST, OR ITS DOCUMENTATION.

The direct vendor makes no warranty or representation, expressed, implied, or statutory with respect to the contents or use of this documentation, and specially disclaims its quality, performance, merchantability, or fitness for any particular purpose. The direct vendor also reserves the right to revise or update device or documentation without obligation to update. For further inquires please contact your direct vendor.