

2 PORT KVM SWITCH

OVERVIEW

The master view BK-82A 2 port KVM (Keyboard, Video, Mouse) switch is a control unit that allows access to two computers from a single console (Keyboard, Monitor and Mouse). Before the development of the master view. The only way to control multiple computer configurations from a single console was through a complex and costly network system. Now with the master view BK-82A you can easily access two computers in a cost effective manner.

Setup is fast and easy; plugging cables into their appropriate ports is all that is entailed. There is no software to configure; there are no installation routines, and no incompatibility problems. Since the master view BK-82A intercepts keyboard input directly, it works on any hardware platform and with all operating systems.

The master view BK-82A provides two convenient methods to access the computers connected to the system. (1) Push button port selection switches located on the unit's front panel. (2) Hotkey combinations entered from the keyboard.

There is no better way to save time and money than with a master view BK-82A installation. Since a single console manages all of the computers, the BK82A setup. (1) Eliminates the expense of having purchase a separate keyboard, Monitor and Mouse for each computer. (2) Saves all the space those extra components would take up. (3) Saves on energy costs. And (4) eliminates the inconvenience and wasted effort involved in constantly moving around from one computer to another.

FEATURES

- ✧ Supports Microsoft intellimouse and the scrolling wheel on most mice
- ✧ Keyboard and mouse emulation for error free booting
- ✧ Easy to install – no software required – standard cables to connect to the computers is all it takes
- ✧ Easy to operate – computer selection via push button switches or hotkeys – auto scan function to monitor computer operation
- ✧ LED display for easy status monitoring
- ✧ Compatible with all operating platforms
- ✧ Caps lock, Num Lock and Scroll lock, states are saved and restored when switching
- ✧ Superior video quality up to 1920x1440 ; DDC ; DDC2 ; DDC2B
- ✧ Compact, sturdy, durable metal housing
- ✧ Efficient, ergonomic design ; logical connector layout
- ✧ Follows PC 99 color specifications
- ✧ Saves time, space, power and equipment costs
- ✧ Non-powered

OPERATION

Controlling all the computers in your BK-82A installation from a single console could not be easier. Two port selection methods that provide instant access to the computers are available:

- ✧ Manual port selection
- ✧ Hotkey port selection

MANUAL PORT SELECTION

With manual port selection, you simply press the port selection switch that corresponds to the port that the computer you want to access is attach to .The selected LED lights to indicate which port is active.

Once Last/Next mode is active, pressing the left shift key [LShift], switches to the previous computer (from the currently active one); pressing [RShift] switches to the next computer in the installation.

NOTE:

1. There is another shorter hotkey combination to produce Last/Next mode switching: simply press the left ctrl key twice in succession [Lctrl+Lctrl] to switch the previous computer: or press the right control key twice in succession [Rctrl+Rctrl] to switch to the next previous computer: this method is available all the time it does not have to first be invoked with [Alt+Ctrl+Shift]
2. While last/Next mode is in effective, none of the other keyboard keys will function. You must exit last/Next mode by pressing the [Spacebar] in order to use the console for anything else.