

NF-308

Wire Fault Tester/Locator with LCD With Port Flashing Function For RJ45/11, BNC, USB



Features

1. Directly hunt 5E, 6E, telephone wire, coaxial cable, USB cable and other cables.
2. Check wiring error in 5E, 6E, coaxial cable, such as open circuit, short circuit, jumper wire, reverse connection.
3. Locate the wiring or connection error.
4. Measure cable length up to 1000m and locate the breakage point.
5. Polarity test function measure DC voltage (0.5-60 V)
6. Memory and storage for calibration data.
7. Automatically time-delay shut off and Low battery alarm function

Attention

- 1 Don't connect high voltage live lines to avoid burning out the machine.
- 2 Put into the right place to avoid hurting others, because of the sharp part.
- 3 Connected the cable to the right port.
- 4 Read the user manual before use it.

Specifications:

NF-308 Transmitter	
Indicator	LCD 53x25 mm, with backlight
Tone frequency	225kHz
Max. distance of transmission	2 km
Max. distance of cable map	1 km
Max. working current	Less than 70mA
Tone mode	2 Tones adjustable
Compatible connectors	RJ11, RJ45, BNC, USB
Max. signal voltage	15Vp-p
Function selection	3 position buttons & 1 power switch
Function and faults LCD display	LCD display (Wire Map, Tone, short, , No adapter, Low battery)
Cable map indication	LCD (#1-#8)
Shielded indication	LCD (#9)
Voltage protection	AC 60V/DC 42V
Battery Type	DC9.0V (Not-Included)
Dimension (L x W x D)	185x80x32mm
NF-308 Receiver	
Frequency	225kHz
The Max. working current	Less than 70mA
Earphone jack	1
LED illumination	2
Battery Type	DC9.0V (Not-Included)
Dimension (L x W x D)	218x46x29 mm
NF-308 Remote unit	
Compatible connectors	RJ45, BNC
Dimension (L x W x D)	107x30x24mm

Specifications are subject to change without prior notice with advancement in technology.

Comparison

Functions	NF-868	NF-308	NF8108
Find Cables	RJ45+RJ11+BNC+USB	RJ45+RJ11+BNC+USB	X
Measure Cable Length	RJ45+RJ11+BNC+USB	RJ45	RJ45
Check Cable Condition	RJ45+RJ11+BNC+USB	RJ45 + BNC	RJ45
Anti-Current Interface	Good	OK	OK
Power Supply	9V Battery	9V Battery	1.5V AA
Display Screen	Black-White	Black-White	Black-White

